

Tech Note 20071030-1-4

Battery Tab Reference List

This document can be used to assist in ordering Tabs for the Cellwatch System. Battery manufacturers can change bolt sizes and types without notice to NDSL, because of this we do not warrant nor guarantee the accuracy of this information. Contact the battery manufacturer or installer to confirm the correct bolt size. This document is not updated regular basis.

Disclaimer: *This document does not replace, nor attempt to replace, any battery documentation supplied by the manufacturer.*

Cellwatch Tabs

Cellwatch Supplies four sizes of battery tabs. All tabs are tinned copper.

Metric	Imperial	Part Number
M5	1/5"	371001
M6	1/4"	371001
M8	5/16"	371006
M10	3/8"	371008
M12	1/2"	371017

NOTE: M5 bolts use the M6 tab. Continue to torque connection to manufacturer specifications.

Tech20071030-1-4 Battery Tab Reference List

Manufacturer	Series	Model	Voltage	Bolt/Post Size	Tab Size Required
Absolyte	IIP Series	All	2 to 12	M6	371001
Absolyte	XL Series	XL2000	4	M6	371001
Absolyte	XL Series	XL3000	4	M6	371001
Absolyte	XL Series	XL4000	4	M6	371001
Absolyte	XL Series	XL5000	4	M6	371001
Absolyte	XL Series	XL6000	4	M6	371001
Alcad	Single Cell - H Range	HB 230P to HB 305P	1.2 / cell	2 x M10	371008
Alcad	Single Cell - H Range	HB 345P to HB 460P	1.2 / cell	3 x M10	371008
Alcad	Single Cell - H Range	HB 510P to HB 615P	1.2 / cell	4 x M10	371008
Alcad	Single Cell - H Range	HB 640P to HB 765P	1.2 / cell	5 x M10	371008
Alcad	Single Cell - H Range	HB 865P & HB 920P	1.2 / cell	6 x M10	371008
Alcad	Single Cell - H Range	HC 185P & HC 210P	1.2 / cell	2 x M10	371008
Alcad	Single Cell - H Range	HC 40P & HC 50P	1.2 / cell	M8	371006
Alcad	Single Cell - H Range	HC 60P to HC 155P	1.2 / cell	M10	371008
Alcad	Single Cell - H Range	HC 9P to HC34P	1.2 / cell	M6	371001
Alcad	Single Cell - L Range	LB 1070P & LB 1280P	1.2 / cell	5 x M10	371008
Alcad	Single Cell - L Range	LB 1450P & LB 1540P	1.2 / cell	6 x M10	371008
Alcad	Single Cell - L Range	LB 385P to LB 510P	1.2 / cell	2 x M10	371008
Alcad	Single Cell - L Range	LB 600P & LB 770P	1.2 / cell	3 x M10	371008
Alcad	Single Cell - L Range	LB 860P to LB 1020P	1.2 / cell	4 x M10	371008
Alcad	Single Cell - L Range	LC 10P to LC 59P	1.2 / cell	M6	371001
Alcad	Single Cell - L Range	LC 310P to LC 355P	1.2 / cell	2 x M10	371008
Alcad	Single Cell - L Range	LC 70P	1.2 / cell	M8	371006
Alcad	Single Cell - L Range	LC 85P to LC 260P	1.2 / cell	M10	371008
Alcad	Single Cell - M Range	MB 1040P & MB 1150P	1.2 / cell	5 x M10	371008
Alcad	Single Cell - M Range	MB 1120P to MB 1390P	1.2 / cell	6 x M10	371008
Alcad	Single Cell - M Range	MB 370P to MB 460P	1.2 / cell	2 x M10	371008
Alcad	Single Cell - M Range	MB 505P to MB 690P	1.2 / cell	3 x M10	371008
Alcad	Single Cell - M Range	MB 740P to MB 920P	1.2 / cell	4 x M10	371008

Tech20071030-1-4 Battery Tab Reference List

Alcad	Single Cell - M Range	MB 965P	1.2 / cell	6 x M10	371008
Alcad	Single Cell - M Range	MC 110P to MC 240P	1.2 / cell	M10	371008
Alcad	Single Cell - M Range	MC 285P to MC 335P	1.2 / cell	2 x M10	371008
Alcad	Single Cell - M Range	MC 70P & MC 90P	1.2 / cell	M8	371006
Alcad	Single Cell - M Range	MC 9P to MC 55P	1.2 / cell	M6	371001
Alcad	Solar Range	PV 45 - PV 1110	1.2	unknown	None Supported
Alcad	Vantage	VN 119-2 to VN 142-3	1.2 / cell	M10	371008
Alcad	Vantage	VN 166-2 to VN 190-3	1.2 / cell	2 x M8	371006
Alcad	Vantage	VN 238-2 to VN 285-3	1.2 / cell	2 x M10	371008
Alcad	Vantage	VN 357-1 to VN 426-1	1.2 / cell	3 x M10	371008
Alcad	Vantage	VN 476-1 +	1.2 / cell	4 x M10	371008
Alcad	Vantage	VN 71-2 to VN 95-3	1.2 / cell	M8	371006
Alcad	Vantage	VN 8-4 to VN 48-6	1.2 / cell	M6	371001
Alcad	XHP - Nickel	XHP 11 - XHP 80	1.2	M10	371008
Alcad	XHP - Nickel	XHP 170 - XHP 320	1.2	2 x M12	None Supported
Alcad	XHP - Nickel	XHP 90 - XHP 150	1.2	M12	None Supported
Alpha Group/Cell	12 V Top Gel	135 AGM-P	12	1/4" - 20 UNC	371001
Alpha Group/Cell	12 V Top Gel	160 AGM	12	1/4" - 20 UNC	371001
Alpha Group/Cell	12 V Top Gel	85 GXL-HP	12	10-32 UNF	371008
Alpha Group/Cell	12 V VRLA	VR12-100C	12	6mm	371001
Alpha Group/Cell	12 V VRLA	VRS12-33C	12		6 371001
Alpha Group/Cell	12 V VRLA	VRS12-50C	12		
Alpha Group/Cell	12 V VRLA	VRS12-75C	12	5/16-18 UNC	371006
Alpha Group/Cell	2V Top VRLA	SMU 2-1000-FR	2	M10	371008
Alpha Group/Cell	2V Top VRLA	SMU 2-100-FR	2	M10	371008
Alpha Group/Cell	2V Top VRLA	SMU 2-1500-FR	2	M10	371008
Alpha Group/Cell	2V Top VRLA	SMU 2-2000-FR	2	M10	371008
Alpha Group/Cell	2V Top VRLA	SMU 2-200-FR	2	M10	371008
Alpha Group/Cell	2V Top VRLA	SMU 2-300-FR	2	M10	371008
Alpha Group/Cell	2V Top VRLA	SMU 2-400-FR	2	M10	371008
Alpha Group/Cell	2V Top VRLA	SMU 2-500-FR	2	M10	371008

Tech20071030-1-4 Battery Tab Reference List

Alpha Group/Cell	2V Top VRLA	SMU 2-600-FR	2	M10	371008
Alpha Group/Cell	2V Top VRLA	SMU 2-800-FR	2	M10	371008
Alpha Group/Cell	Front Access	SMU-F 12-105-FR	12		6 371001
Alpha Group/Cell	Front Access	SMU-F 12-125-F	12		6 371001
Alpha Group/Cell	Front Access	SMU-F 12-155-F	12		6 371001
Alpha Group/Cell	Front Access	SMU-F 12-170-FR	12		6 371001
Alpha Group/Cell	Front Access	SMU-F 12-50-FR	12		6 371001
Alpha Group/Cell	Front Access	SMU-F 12-75-FR	12		6 371001
Alpha Group/Cell	Front Access	SMU-F 12-85-FR	12		6 371001
Alpha Group/Cell		165 GXL	12		
Alpha Group/Cell		180 GXL	12		
Alpha Group/Cell		190 GOLD-HP	12	1/4" - 20 UNC	371001
Alpha Group/Cell		195 GXL-FT	12	16mm M6	371001
Alpha Group/Cell		210 GXL-HP	12		
Alpha Group/Cell		215 GOLD-HP	12	1/4" - 20 UNC	371001
Alpha Group/Cell		225 AGM-FT	12	16mm M6	371001
Alpha Group/Cell		85 GXL-HP	12	10-32 UNF	371008
Alpha Group/Cell		GXL-FT	12	16mm M6	371001
Alpha Group/Cell		NI-CD-XLUCNT	2	2 thru 10 - M8 thru M10	371006, 371008
B.B. Battery	BP - General Use	BP1.0-6	6	Tab	None Supported
B.B. Battery	BP - General Use	BP1.2-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP1.2-6	6	Tab	None Supported
B.B. Battery	BP - General Use	BP10-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP10-4	4	Tab	None Supported
B.B. Battery	BP - General Use	BP10-6	6	Tab	None Supported
B.B. Battery	BP - General Use	BP120-12	12	M6	371001
B.B. Battery	BP - General Use	BP12-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP12-6	6	Tab	None Supported
B.B. Battery	BP - General Use	BP13-6H	6		
B.B. Battery	BP - General Use	BP13-6S	6	Tab	None Supported
B.B. Battery	BP - General Use	BP160-12	12	M8	371006

Tech20071030-1-4 Battery Tab Reference List

B.B. Battery	BP - General Use	BP17-12	12	M5 or Tab	None Supported
B.B. Battery	BP - General Use	BP2.3-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP230-12	12	M8	371006
B.B. Battery	BP - General Use	BP26-12	12	M5 or Tab	None Supported
B.B. Battery	BP - General Use	BP28-12	12	M5 or Tab	None Supported
B.B. Battery	BP - General Use	BP3.6-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP3-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP33-12F	12	M6	371001
B.B. Battery	BP - General Use	BP33-12H	12	M6	371001
B.B. Battery	BP - General Use	BP33-12S	12	M6	371001
B.B. Battery	BP - General Use	BP33-6	6	M5 and Tab	None Supported
B.B. Battery	BP - General Use	BP35-12F	12	M6	371001
B.B. Battery	BP - General Use	BP35-12H	12	M6	371001
B.B. Battery	BP - General Use	BP35-12S	12	M6	371001
B.B. Battery	BP - General Use	BP3-6	6	Tab	None Supported
B.B. Battery	BP - General Use	BP4.5-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP4.5-6	6	Tab	None Supported
B.B. Battery	BP - General Use	BP40-12	12	M5 or M6	371001
B.B. Battery	BP - General Use	BP4-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP4-6	6	Tab	None Supported
B.B. Battery	BP - General Use	BP5-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP5-6	6	Tab	None Supported
B.B. Battery	BP - General Use	BP65-12	12	M6	371001
B.B. Battery	BP - General Use	BP7.5-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP7-12	12	Tab	None Supported
B.B. Battery	BP - General Use	BP7-6	6	Tab	None Supported
B.B. Battery	BP - General Use	BP8-12VL	12	Tab	None Supported
B.B. Battery	BP - General Use	BP8-12VS	12	Tab	None Supported
B.B. Battery	BP - General Use	BP8-6	6	Tab	None Supported
B.B. Battery	BP - General Use	BP8-6V	6	Tab	None Supported
B.B. Battery	BP - General Use	BP90-12	12	M6	371001

Tech20071030-1-4 Battery Tab Reference List

B.B. Battery	BPL	BPL110-12	12	M6	371001
B.B. Battery	BPL	BPL12-12	12	Tab	None Supported
B.B. Battery	BPL	BPL150-12	12	M8	371006
B.B. Battery	BPL	BPL17-12	12	M5 or Tab	None Supported
B.B. Battery	BPL	BPL210-12	12	M8	371006
B.B. Battery	BPL	BPL26-12	12	M5 or Tab	None Supported
B.B. Battery	BPL	BPL28-12	12	M5 or Tab	None Supported
B.B. Battery	BPL	BPL3.3-12	12	Tab	None Supported
B.B. Battery	BPL	BPL33-12	12	M6	371001
B.B. Battery	BPL	BPL40-12	12	M5 or M6	371001
B.B. Battery	BPL	BPL65-12	12	M5 or M6	371001
B.B. Battery	BPL	BPL7-12	12	Tab	None Supported
B.B. Battery	BPL	BPL85-12	12	M5 or M6	371001
B.B. Battery	EB	EB12-12	12	Tab	None Supported
B.B. Battery	EB	EB20-12	12	M5 (Supply M6)	371001
B.B. Battery	EB	EB50-12	12	M6	371001
B.B. Battery	EP	EP100-12	12	M6	371001
B.B. Battery	EP	EP12-12	12	Tab	None Supported
B.B. Battery	EP	EP17-12	12	M5 or Tab	None Supported
B.B. Battery	EP	EP26-12	12	M5 or Tab	None Supported
B.B. Battery	EP	EP28-12	12	M5 or Tab	None Supported
B.B. Battery	EP	EP33-12	12	M6	371001
B.B. Battery	EP	EP40-12	12	M5, M6 or Tab	371001
B.B. Battery	EP	EP65-12	12	M6	371001
B.B. Battery	EP	EP7-12	12	Tab	None Supported
B.B. Battery	EP	EP80-12	12	M5 or M6	371001
B.B. Battery	EVP	EVP12-12	12	Tab	None Supported
B.B. Battery	EVP	EVP20-12	12	M5 or Tab	None Supported
B.B. Battery	EVP	EVP26-12	12	M5 or Tab	None Supported
B.B. Battery	EVP	EVP35-12	12	M6	371001
B.B. Battery	EVP	EVP44-12	12	M5 or M6	371001

Tech20071030-1-4 Battery Tab Reference List

B.B. Battery	EVP	EVP70-12	12	M6	371001
B.B. Battery	EVP	EVP7-12	12	Tab	None Supported
B.B. Battery	HR - High Rate Use	HR15-12	12	Tab	None Supported
B.B. Battery	HR - High Rate Use	HR22-12	12	M5 or Tab	None Supported
B.B. Battery	HR - High Rate Use	HR33-12	12	M5 or Tab	None Supported
B.B. Battery	HR - High Rate Use	HR40-12	12	M5, M6 or Tab	371001
B.B. Battery	HR - High Rate Use	HR4-12	12	Tab	None Supported
B.B. Battery	HR - High Rate Use	HR5.5-12	12	Tab	None Supported
B.B. Battery	HR - High Rate Use	HR5.8-12	12	Tab	None Supported
B.B. Battery	HR - High Rate Use	HR50-12	12	M5 or M6	371001
B.B. Battery	HR - High Rate Use	HR6-12	12	Tab	None Supported
B.B. Battery	HR - High Rate Use	HR75-12	12	M6	371001
B.B. Battery	HR - High Rate Use	HR8-12	12	Tab	None Supported
B.B. Battery	HR - High Rate Use	HR9-12	12	M5 or Tab	None Supported
B.B. Battery	HR - High Rate Use	HR9-6	6	Tab	None Supported
B.B. Battery	MPL	MPL55-12(S/H)	12	M6	371001
B.B. Battery	MPL	MPL80-12(S/H)	12	M6	371001
B.B. Battery	MPL	MPL90-12(S/H)	12	M6	371001
B.B. Battery	RT	BP4.5-12RT	12		
B.B. Battery	RT	BP5.5-12RT	12		
B.B. Battery	RT	BP7-12RT	12		
C & D	C & D	UPS12-100FR	12	M6	371001
C & D	C & D	UPS12-140	12	M6	371001
C & D	C & D	UPS12-200	12	M6	371001
C & D	C & D	UPS12-270	12	M8	371006
C & D	C & D	UPS12-310	12	M8	371006
C & D	C & D	UPS12-370	12	M8	371006
C & D	C & D	UPS12-475	12	M8	371006
C & D	C & D	UPS6-620	6	M8	371006
CSB	EVX Series	EVX 121000	12	6.5 mm	371001
CSB	EVX Series	EVX 12120	12	F1/F2 Tab	None Supported

Tech20071030-1-4 Battery Tab Reference List

CSB	EVX Series	EVX 12170	12	5.5 mm	None Supported
CSB	EVX Series	EVX 12200	12	M5 (Supply M6)	371001
CSB	EVX Series	EVX 12260	12	5.5 mm	None Supported
CSB	EVX Series	EVX 12300	12	M5 (Supply M6)	371001
CSB	EVX Series	EVX 12340	12	6.5 mm	371001
CSB	EVX Series	EVX 12400	12	5.5 mm	None Supported
CSB	EVX Series	EVX 12520	12	6.5 mm	371001
CSB	EVX Series	EVX 12650	12	6.5 mm	371001
CSB	EVX Series	EVX 12750	12	5/16"	371006
CSB	GP Series	GP 121000	12	M6	371001
CSB	GP Series	GP 12120	12	F1/F2 Tab	None Supported
CSB	GP Series	GP 12170	12	5.5 mm	None Supported
CSB	GP Series	GP 12200	12	M5 (Supply M6)	371001
CSB	GP Series	GP 1222	12	F1/F2 Tab	None Supported
CSB	GP Series	GP 12260	12	5.5 mm	None Supported
CSB	GP Series	GP 12340	12	6.5 mm	371001
CSB	GP Series	GP 12400	12	5.5 mm	None Supported
CSB	GP Series	GP 1245	12	F1/F2 Tab	None Supported
CSB	GP Series	GP 12650	12	6.5 mm	371001
CSB	GP Series	GP 1272	12	F1/F2 Tab	None Supported
CSB	GP Series	GP 6120	6	F1/F2 Tab	None Supported
CSB	GP Series	GP 645	6	F1/F2 Tab	None Supported
CSB	GP Series	GP 672	6	F1/F2 Tab	None Supported
CSB	GPL Series	GPL 121000	12	M6	371001
CSB	GPL Series	GPL 12120	12	F1/F2 Tab	None Supported
CSB	GPL Series	GPL 12260	12	M5 (Supply M6)	371001
CSB	GPL Series	GPL 12400	12	M5 (Supply M6)	371001
CSB	GPL Series	GPL 12520	12	M6	371001
CSB	GPL Series	GPL 1272	12	F1/F2 Tab	None Supported
CSB	GPL Series	GPL 12750	12	M6	371001
CSB	GPL Series	GPL 12880	12	M6	371001

Tech20071030-1-4 Battery Tab Reference List

CSB	GPL Series	GPL 672	6	F1/F2 Tab	None Supported
CSB	HC Series	HC 1217W	12	C1 Faston Tab 187/250	None Supported
CSB	HC Series	HC 1221W	12	C1 Faston Tab 187/250	None Supported
CSB	HC Series	HC 1225W	12	C1 Faston Tab 187/250	None Supported
CSB	HC Series	HC 1228W	12	C1 Faston Tab 187/250	None Supported
CSB	HR Series	HR 12120W	12	M5 (Supply M6)	371001
CSB	HR Series	HR 1221W	12	F1/F2 Tab	None Supported
CSB	HR Series	HR 1224W	12	F1/F2 Tab	None Supported
CSB	HR Series	HR 1234W	12	F2 Faston Tab 250	None Supported
CSB	HR Series	HR 1251W	12	F1/F2 Tab	None Supported
CSB	HRL Series	HRL 1210W	12	F2 Faston Tab 250	None Supported
CSB	HRL Series	HRL 12110W	12	M5 (Supply M6)	371001
CSB	HRL Series	HRL 12150W	12	M6	371001
CSB	HRL Series	HRL 12200W	12	M6	371001
CSB	HRL Series	HRL 1223W	12	F2 Faston Tab 250	None Supported
CSB	HRL Series	HRL 12280W	12	M6	371001
CSB	HRL Series	HRL 12330W	12	M6	371001
CSB	HRL Series	HRL 1234W	12	F2 Faston Tab 250	None Supported
CSB	HRL Series	HRL 12390W	12	M6	371001
CSB	HRL Series	HRL 12500W	12	M6	371001
CSB	HRL Series	HRL 1280W	12	M5 (Supply M6)	371001
CSB	HRL Series	HRL 634W	6	F2 Faston Tab 250	None Supported
CSB	MSJ Series	MSJ 1000	2	Recessed Terminal	None Supported
CSB	MSJ Series	MSJ 150	2	Recessed Terminal	None Supported
CSB	MSJ Series	MSJ 200	2	Recessed Terminal	None Supported
CSB	MSJ Series	MSJ 260	2	Recessed Terminal	None Supported
CSB	MSJ Series	MSJ 300	2	Recessed Terminal	None Supported
CSB	MSJ Series	MSJ 350	2	Recessed Terminal	None Supported
CSB	MSJ Series	MSJ 400	2	Recessed Terminal	None Supported
CSB	MSJ Series	MSJ 500	2	Recessed Terminal	None Supported
CSB	MSJ Series	MSJ 650	2	Recessed Terminal	None Supported

Tech20071030-1-4 Battery Tab Reference List

CSB	MSJ Series	MSJ 800	2	Recessed Terminal	None Supported
CSB	MU Series	MU 1000	2	Recessed Terminal	None Supported
CSB	MU Series	MU 1500	2	Recessed Terminal	None Supported
CSB	TPL Series	TPL 121000	12	M6	371001
CSB	TPL Series	TPL 121250	12	M6	371001
CSB	TPL Series	TPL 121350	12	M6	371001
CSB	TPL Series	TPL 121500	12	M6	371001
CSB	TPL Series	TPL 12800	12	M6	371001
CSB	TPL Series	TPL 12900	12	M6	371001
Deka	Solar Photovoltaic Batteries	8G22NF	12	5/16" bolt & hex nut	371006
Deka	Solar Photovoltaic Batteries	8G24	12	5/16" bolt & hex nut	371006
Deka	Solar Photovoltaic Batteries	8G27	12	5/16" bolt & hex nut	371006
Deka	Solar Photovoltaic Batteries	8G30H	12	3/8" flag terminal	371008
Deka	Solar Photovoltaic Batteries	8G31	12	3/8" ss stud	371008
Deka	Solar Photovoltaic Batteries	8G4D	12	SAE Post	None Supported
Deka	Solar Photovoltaic Batteries	8G8D	12	SAE Post	None Supported
Deka	Solar Photovoltaic Batteries	8GGC2	12	5/16" bolt & hex nut	371006
Deka	Solar Photovoltaic Batteries	8GU1	12	round holes	None Supported
Deka	Solar Photovoltaic Batteries	8GU1H	12	round holes	None Supported
Deka	Solar Photovoltaic Batteries - Flooded Monoblock	8C11(D)	6	11/32" DIA	None Supported
Deka	Solar Photovoltaic Batteries - Flooded Monoblock	8L16(D)	6	5/16", 3/8", 11/32", SAE	371006, 371008
Deka	Solar Photovoltaic Batteries - Flooded Monoblock	9C11(D)	6	11/32" DIA	None Supported
Deka	Solar Photovoltaic Batteries - Flooded Monoblock	DC27	12	Marine	None Supported
Deka	Solar Photovoltaic Batteries - Flooded Monoblock	GC15G	6	11/32" DIA	None Supported
Deka	Unigy	4DHR6500(S)	12	1/4" x 20	371001
Deka	Unigy	HR5500ET	12	1/4" x 20	371001
Deka	Unigy I	12AVR-100	12	1/4" x 20	371001
Deka	Unigy I	12AVR100-3ET	12	1/4" x 20	371001
Deka	Unigy I	12AVR-125L/LLP	12	1/4" x 20	371001
Deka	Unigy I	12AVR-130	12	1/4" x 20	371001
Deka	Unigy I	12AVR-145L/LLP	12	1/4" x 20	371001

Tech20071030-1-4 Battery Tab Reference List

Deka	Unigy I	12AVR-150ET	12	1/4" x 20	371001
Deka	Unigy I	12AVR-30	12	Inserted Post #10-32	None Supported
Deka	Unigy I	12AVR-40	12	Inserted Post #10-32	None Supported
Deka	Unigy I	12AVR-75	12	1/4" x 19	371001
Deka	Unigy I	12AVR-90	12	1/4" x 20	371001
Deka	Unigy I	12GVR-100	12	1/4" x 20	371001
Deka	Unigy I	12GVR-75	12	1/4" x 20	371001
Deka	Unigy II	AVR125-2000	2	1/4" x 20	371001
Deka	Unigy II	AVR45	2	1/4" x 20	371001
Deka	Unigy II	AVR75	2	1/4" x 20	371001
Deka	Unigy II	AVR85	2	1/4" x 20	371001
Deka	Unigy II	AVR95	2	1/4" x 20	371001
Deka	Unigy II	NC4-2000	2	1/4" x 20	371001
Enersys	DataSafe	CX-316SS	2	1/4 to 1/2	371001, 371006, 371008
Enersys	DataSafe	DX Series	4 to 8	1/4 to 1/2	371001, 371006, 371008
Enersys	DataSafe	DXC Series	4 to 8	1/4 to 1/2	371001, 371006, 371008
Enersys	DataSafe	ES Series	2	1/4 to 1/2	371001, 371006, 371008
Enersys	DataSafe	HX205	12	M6	371001
Enersys	DataSafe	HX300	12	M6	371001
Enersys	DataSafe	HX330	12	M6	371001
Enersys	DataSafe	HX400	12	M6	371001
Enersys	DataSafe	HX500	12	M6	371001
Enersys	DataSafe	JX225		M6	371001
Enersys	DataSafe	JX375		M6	371001
Enersys	Genesis	NP100-12FR	12	M6 available	371001
Enersys	Genesis	NP120-12FR	12	7mm	371006
Enersys	Genesis	NP150-12FR	12	7mm	371006
Enersys	Genesis	NP18-12BFR	12	5.5mm	371001
Enersys	Genesis	NP200-12FR	12	7mm	371006
Enersys	Genesis	NP33-12FR	12	M6 available	371001
Enersys	Genesis	NP38-12R	12	10-32 UNF	371008

Tech20071030-1-4 Battery Tab Reference List

Energys	Genesis	NP55-12FR	12	M6 available	371001
Energys	Genesis	NP65-12FR	12	7mm	371006
Energys	Genesis	NP75-12FR	12	M6 available	371001
Energys	Genesis	NP90-12FR	12	7mm	371006
Energys	Genesis	NP-GEL30-12	12	M6, 8.3mm	371001, 371006
Energys	Genesis	NP-GEL50-12	12	M6, 8.3mm	371001, 371006
Energys	Genesis	NP-GEL70-12	12	M6, 8.3mm	371001, 371006
Energys	Genesis	NP-GEL90-12	12	M6, 8.3mm	371001, 371006
Energys	Genesis	NPX-100R	12	10-32 UNF	371008
Energys	Genesis	NPX-150R	12	10-32 UNF	371008
Energys	Genesis	NPX-80FR	12	5.5mm	371001
Energys	Genesis	XE Series		M6	371001
Energys	PowerSafe	12TX105F	12	M8 M	371006
Energys	PowerSafe	12V100F	12	M6 M	371001
Energys	PowerSafe	12V105F	12	M6 M	371001
Energys	PowerSafe	12V125F	12	M6 M	371001
Energys	PowerSafe	12V155FS	12	M6 M	371001
Energys	PowerSafe	12V170F	12	M6 M	371001
Energys	PowerSafe	12V30F	12	M8 F	371006
Energys	PowerSafe	12V38F	12	M8 F	371006
Energys	PowerSafe	12V45	12	M6 F	371001
Energys	PowerSafe	12V55	12	M6 F	371001
Energys	PowerSafe	12V62F	12	M8 F	371006
Energys	PowerSafe	12V70	12	M6 F	371001
Energys	PowerSafe	12V80	12	M6 F	371001
Energys	PowerSafe	12V92F	12	M8 F	371006
Energys	PowerSafe	12VX100F	12	2 x M6 M	371001
Energys	PowerSafe	2V200	2	M8 F	371006
Energys	PowerSafe	2V275	2	M8 F	371006
Energys	PowerSafe	2V310	2	M8 M	371006
Energys	PowerSafe	2V320	2	M8 F	371006

Tech20071030-1-4 Battery Tab Reference List

Energys	PowerSafe	2V400/2	2	M8 F	371006
Energys	PowerSafe	2V460/2	2	M8 M	371006
Energys	PowerSafe	2V460/6	2	M8 M	371006
Energys	PowerSafe	2V500/2	2	M8 F	371006
Energys	PowerSafe	2V500/6	2	M8 F	371006
Energys	PowerSafe	4TX105	4	M8 M	371006
Energys	PowerSafe	4V105	4	M8 M	371006
Energys	PowerSafe	4V155	4	M8 M	371006
Energys	PowerSafe	4V230	4	M8 M	371006
Energys	PowerSafe	4VX105	4	2 x M8 M	371006
Energys	PowerSafe	6TX105	6	M8 M	371006
Energys	PowerSafe	6V105	6	M8 M	371006
Energys	PowerSafe	6V130	6	M8 F	371006
Energys	PowerSafe	6V155	6	M8 M	371006
Energys	PowerSafe	6V165/2	6	M8 F	371006
Energys	PowerSafe	6VX105	6	2 x M8 M	371006
Energys	PowerSafe	6VX155	6	6 x M8 M	371006
Energys	PowerSafe	8V100F	8	M6 M	371001
Energys	PowerSafe	8VX100F	8	2 x M6 M	371001
Energys	PowerSafe	DDM100-21	2	M8	371006
Energys	PowerSafe	DDM100-25	2	M8	371006
Energys	PowerSafe	DDM100-27	2	M8	371006
Energys	PowerSafe	DDM100-33	2	M8	371006
Energys	PowerSafe	DDM125-25	2	M8	371006
Energys	PowerSafe	DDM125-27	2	M8	371006
Energys	PowerSafe	DDM125-33	2	M8	371006
Energys	PowerSafe	DDM50-09	2	M8	371006
Energys	PowerSafe	DDM50-13	2	M8	371006
Energys	PowerSafe	DDM50-17	2	M8	371006
Energys	PowerSafe	DDM85-13	2	M8	371006
Energys	PowerSafe	DDM85-15	2	M8	371006

Tech20071030-1-4 Battery Tab Reference List

Energys	PowerSafe	DDM85-21	2	M8	371006
Energys	PowerSafe	DDM85-25	2	M8	371006
Energys	PowerSafe	DDM85-27	2	M8	371006
Energys	PowerSafe	DDM85-33	2	M8	371006
Energys	PowerSafe	SBS 110	6	M8 M	371006
Energys	PowerSafe	SBS 130	6	M8 M	371006
Energys	PowerSafe	SBS 145	12	M8 F	371006
Energys	PowerSafe	SBS 145F	12	M6 M	371001
Energys	PowerSafe	SBS 15	12	M6 M	371001
Energys	PowerSafe	SBS 30	12	M6 M	371001
Energys	PowerSafe	SBS 300	2	M8 M	371006
Energys	PowerSafe	SBS 390	2	M8 M	371006
Energys	PowerSafe	SBS 40	12	M6 M	371001
Energys	PowerSafe	SBS 60	12	M6 M	371001
Energys	PowerSafe	SBS 8	12	M4 F	None Supported
Energys	PowerSafe	SBS B10	12	M8 F	371006
Energys	PowerSafe	SBS B10F	12	M6 M	371001
Energys	PowerSafe	SBS B14	12	M8 F	371006
Energys	PowerSafe	SBS B14F	12	M6 M	371001
Energys	PowerSafe	SBS B8	12	M8 F	371006
Energys	PowerSafe	SBS B8F	12	M6 M	371001
Energys	PowerSafe	SBS C11	12	M8 F	371006
Energys	PowerSafe	SBS C11F	12	M6 M	371001
Energys	PowerSafe	SBS J13	12	M6 F	371001
Energys	PowerSafe	SBS J16	12	M6 F	371001
Energys	PowerSafe	SBS J30	12	M6 F	371001
Energys	PowerSafe	SBS J40	12	M6 F	371001
Energys	PowerSafe	SBS J70	12	M6 F	371001
Energys	Varta	RH 10	2	M10	371008
Energys	Varta	RH 100	2	M8	371006
Energys	Varta	RH 125	2	M8	371006

Tech20071030-1-4 Battery Tab Reference List

Energys	Varta	RH 150	2	M8	371006
Energys	Varta	RH 185	2	M8	371006
Energys	Varta	RH 20	2	M10	371008
Energys	Varta	RH 200	2	M8	371006
Energys	Varta	RH 235	2	M8	371006
Energys	Varta	RH 250	2	M8	371006
Energys	Varta	RH 280	2	M8	371006
Energys	Varta	RH 30	2	M8	371006
Energys	Varta	RH 300	2	M10	371008
Energys	Varta	RH 320	2	M10	371008
Energys	Varta	RH 360	2	M10	371008
Energys	Varta	RH 390	2	M10	371008
Energys	Varta	RH 40	2	M8	371006
Energys	Varta	RH 420	2	M10	371008
Energys	Varta	RH 450	2	M10	371008
Energys	Varta	RH 480	2	M10	371008
Energys	Varta	RH 50	2	M8	371006
Energys	Varta	RH 520	2	M10	371008
Energys	Varta	RH 560	2	M10	371008
Energys	Varta	RH 600	2	M10	371008
Energys	Varta	RH 640	2	M10	371008
Energys	Varta	RH 65	2	M8	371006
Energys	Varta	RH 700	2	M10	371008
Energys	Varta	RH 750	2	M10	371008
Energys	Varta	RH 80	2	M8	371006
Energys	Varta	RH 800	2	M10	371008
Exide	Classic (Flooded)	Energy Block	6 to 12	M8	371006
Exide	Classic (Flooded)	HCT Series	2	M10	371008
Exide	Classic (Flooded)	MCT Series	2	SS M10	371008
Exide	Classic (Flooded)	MCX Series	2	SS M10	371008
Exide	Classic (Flooded)	NCN Series	2	M10	371008

Tech20071030-1-4 Battery Tab Reference List

Exide	Classic (Flooded)	NCT Series	2	M10	371008
Exide	Classic (Flooded)	NCX Series	2	M10	371008
Exide	Classic (Flooded)	PDQ	4 to 8	M10	371008
Exide	Classic (Flooded)	T-Block	2	M8	371006
Exide	Sunlyte	12-5000X	12	M6	371001
GNB Classic	Flooded T-Bloc	3-TCX-200	6	M8	371006
GNB Classic	Flooded T-Bloc	3-TCX-250	6	M8	371006
GNB Classic	Flooded T-Bloc	3-TCX-300	6	M8	371006
GNB Classic	Flooded T-Bloc	6-TCX-050	12	M8	371006
GNB Classic	Flooded T-Bloc	6-TCX-100	12	M8	371006
GNB Classic	Flooded T-Bloc	6-TCX-150	12	M8	371006
Marathon	L Series	L12V15	12	M6	371001
Marathon	L Series	L12V32	12	M6	371001
Marathon	L Series	L12V42	12	M6	371001
Marathon	L Series	L12V55	12	M6	371001
Marathon	L Series	L12V80	12	M8	371006
Marathon	L Series	L2V220	2	M8	371006
Marathon	L Series	L2V270	2	M8	371006
Marathon	L Series	L2V320	2	M8	371006
Marathon	L Series	L2V375	2	M8	371006
Marathon	L Series	L2V470	2	M8	371006
Marathon	L Series	L2V520	2	M8	371006
Marathon	L Series	L2V575	2	M8	371006
Marathon	L Series	L6V110	6	M8	371006
Marathon	L Series	L6V160	6	M8	371006
Marathon	M FT (Front Terminal)	All	6 to 12	M6	371001
Marathon	P Series	P12V1220	12	M6	371001
Marathon	P Series	P12V1575	12	M6	371001
Marathon	P Series	P12V2130	12	M8	371006
Marathon	P Series	P12V570	12	M6	371001
Marathon	P Series	P12V600	12	M6	371001

Tech20071030-1-4 Battery Tab Reference List

Marathon	P Series	P12V875	12	M6	371001
Marathon	P Series	P6V1700	6	M8	371006
Marathon	P Series	P6V2030	6	M8	371006
Odyssey	Extreme	PC 1200	12	M6	371001
Odyssey	Extreme	PC 1500/34	12	SAE 3/8	None Supported
Odyssey	Extreme	PC 1500/34-78	12	3/8" and 3/8" 16	371008
Odyssey	Extreme	PC 1500/34M	12	3/8" and 5/16"	371006, 371008
Odyssey	Extreme	PC 1700	12	M6 or 5/16" or SAE 3/8"	371001, 371006
Odyssey	Extreme	PC 1700/65	12	M6 or 5/16" or SAE 3/8"	371001, 371006
Odyssey	Extreme	PC 2150/31	12	SAE or 3/8" 16	None Supported
Odyssey	Extreme	PC 2250	12	3/8"	371008
Odyssey	Extreme	PC 310	12	M4	None Supported
Odyssey	Extreme	PC 535	12	M6	371001
Odyssey	Extreme	PC 545	12	M6	371001
Odyssey	Extreme	PC 625	12	M6	371001
Odyssey	Extreme	PC 680	12	M6	371001
Odyssey	Extreme	PC 925	12	M6	371001
Power Fit	S300 Series	S306-10	6	N/A	
Power Fit	S300 Series	S312-07	12	N/A	
Power Fit	S300 Series	S312-18	12	N/A	
Power Fit	S300 Series	S312-25	12	M5 (Supply M6)	371001
Power Fit	S300 Series	S312-40	12	M5 (Supply M6)	371001
Power Fit	S300 Series	S312-55	12	M6	371001
Power Fit	S300 Series	S312-65	12	M6	371001
Power Fit	S500 Series	S506-130	6	M8	371006
Power Fit	S500 Series	S506-185	6	M8	371006
Power Fit	S500 Series	S512-90	12	M8	371006
Relay Gel	Relay Gel	All	12	M6	371001
Sonnenschein	A200	A204/1 K	4	K-Terminal (Contact)	None Supported
Sonnenschein	A200	A206/1 S	6	Tab	None Supported
Sonnenschein	A200	A206/6,5 S	6	Tab	None Supported

Tech20071030-1-4 Battery Tab Reference List

Sonnenschein	A200	A208/2,5	8	Tab	None Supported
Sonnenschein	A200	A208/3,8 S	8	Tab	None Supported
Sonnenschein	A200	A212/2,5 S	12	Tab	None Supported
Sonnenschein	A400	A406/165 F10	6	M10	371008
Sonnenschein	A400	A406/165A	6	A-Terminal (SAE)	371001
Sonnenschein	A400	A412/100 A	12	A-Terminal (SAE)	371001
Sonnenschein	A400	A412/100 F10	12	M10	371008
Sonnenschein	A400	A412/12 SR	12	Tab	None Supported
Sonnenschein	A400	A412/120 A	12	A-Terminal (SAE)	371001
Sonnenschein	A400	A412/120 F10	12	M10	371008
Sonnenschein	A400	A412/180 A	12	A-Terminal (SAE)	371001
Sonnenschein	A400	A412/180 F10	12	M10	371008
Sonnenschein	A400	A412/20 G5	12	M5 (Supply M6)	371001
Sonnenschein	A400	A412/32 F10	12	M10	371008
Sonnenschein	A400	A412/32 G6	12	M6	371001
Sonnenschein	A400	A412/5,5 SR	12	Tab	None Supported
Sonnenschein	A400	A412/50 A	12	A-Terminal (SAE)	371001
Sonnenschein	A400	A412/50 F10	12	M10	371008
Sonnenschein	A400	A412/50 G6	12	M6	371001
Sonnenschein	A400	A412/65 F10	12	M10	371008
Sonnenschein	A400	A412/65 G6	12	M6	371001
Sonnenschein	A400	A412/8,5 SR	12	Tab	None Supported
Sonnenschein	A400	A412/85 F10	12	M10	371008
Sonnenschein	A400	A412/90 A	12	A-Terminal (SAE)	371001
Sonnenschein	A400	A412/90 F10	12	M10	371008
Sonnenschein	A400 FT (Front Terminal)	A412/120 FT	12	M8	371006
Sonnenschein	A500	A502/10 S	2	Tab	None Supported
Sonnenschein	A500	A504/3,5 S	4	Tab	None Supported
Sonnenschein	A500	A506/1,2 S	6	Tab	None Supported
Sonnenschein	A500	A506/10 S*	6	Tab	None Supported
Sonnenschein	A500	A506/4,2 S	6	Tab	None Supported

Tech20071030-1-4 Battery Tab Reference List

Sonnenschein	A500	A506/6,5 S	6	Tab	None Supported
Sonnenschein	A500	A508/3,5 S	8	Tab	None Supported
Sonnenschein	A500	A512/1,2 S*	12	Tab	None Supported
Sonnenschein	A500	A512/10 S	12	Tab	None Supported
Sonnenschein	A500	A512/115 A	12	A-Terminal (SAE)	371001
Sonnenschein	A500	A512/120 A	12	A-Terminal (SAE)	371001
Sonnenschein	A500	A512/140 A	12	A-Terminal (SAE)	371001
Sonnenschein	A500	A512/16 G5	12	M5 (Supply M6)	371001
Sonnenschein	A500	A512/2 S	12	Tab	None Supported
Sonnenschein	A500	A512/200A	12	A-Terminal (SAE)	371001
Sonnenschein	A500	A512/25 G5	12	M5 (Supply M6)	371001
Sonnenschein	A500	A512/3,5 S	12	Tab	None Supported
Sonnenschein	A500	A512/30 G6	12	M5 (Supply M6)	371001
Sonnenschein	A500	A512/40 A	12	A-Terminal (SAE)	371001
Sonnenschein	A500	A512/40 G6	12	M6	371001
Sonnenschein	A500	A512/55 A	12	A-Terminal (SAE)	371001
Sonnenschein	A500	A512/6,5 S	12	Tab	None Supported
Sonnenschein	A500	A512/60 A	12	A-Terminal (SAE)	371001
Sonnenschein	A500	A512/60 G6	12	M6	371001
Sonnenschein	A500	A512/65 A	12	A-Terminal (SAE)	371001
Sonnenschein	A500	A512/65 G6	12	M6	371001
Sonnenschein	A500	A512/85 A	12	A-Terminal (SAE)	371001
Sonnenschein	A600 Solar Series	All OPzV	2	M8	371006
Sonnenschein	OGiV / A700	4V 7 OGiV 224 / A704/245	4	M8	371006
Sonnenschein	OGiV / A700	4V 8 OGiV 256 / A704/280	4	M8	371006
Sonnenschein	OGiV / A700	6V 1 OGiV 18 / A706/21	6	M5 (Supply M6)	371001
Sonnenschein	OGiV / A700	6V 2 OGiV 36 / A706/42	6	M5 (Supply M6)	371001
Sonnenschein	OGiV / A700	6V 3 OGiV 54 / A706/63	6	M8	371006
Sonnenschein	OGiV / A700	6V 4 OGiV 128 / A706/140	6	M8	371006
Sonnenschein	OGiV / A700	6V 4 OGiV 72 / A706/84	6	M8	371006
Sonnenschein	OGiV / A700	6V 5 OGiV 160 / A706/175	6	M8	371006

Tech20071030-1-4 Battery Tab Reference List

Sonnenschein	OGiV / A700	6V 5 OGiV 90 / A706/108	6	M8	371006
Sonnenschein	OGiV / A700	6V 6 OGiV 108 / A706/126	6	M8	371006
Sonnenschein	OPzV / A600	10 OPzV 1000 / A602/1000	2	M8	371006
Sonnenschein	OPzV / A600	12 OPzV 1200 / A602/1200	2	M8	371006
Sonnenschein	OPzV / A600	12 OPzV 1500 / A602/1500	2	M8	371006
Sonnenschein	OPzV / A600	12V 2 OPzV 100 / A612/100	12	M8	371006
Sonnenschein	OPzV / A600	12V 3 OPzV 150 / A612/150	12	M8	371006
Sonnenschein	OPzV / A600	16 OPzV 2000 / A602/2000	2	M8	371006
Sonnenschein	OPzV / A600	20 OPzV 2500 / A602/2500	2	M8	371006
Sonnenschein	OPzV / A600	24 OPzV 3000 / A602/3000	2	M8	371006
Sonnenschein	OPzV / A600	4 OPzV 200 / A602/200	2	M8	371006
Sonnenschein	OPzV / A600	5 OPzV 250 / A602/250	2	M8	371006
Sonnenschein	OPzV / A600	5 OPzV 350 / A602/350	2	M8	371006
Sonnenschein	OPzV / A600	6 OPzV 300 / A602/300	2	M8	371006
Sonnenschein	OPzV / A600	6 OPzV 420 / A602/420	2	M8	371006
Sonnenschein	OPzV / A600	6 OPzV 600 / A602/600	2	M8	371006
Sonnenschein	OPzV / A600	6V 4 OPzV 200 / A606/200	6	M8	371006
Sonnenschein	OPzV / A600	6V 6 OPzV 300 / A606/300	6	M8	371006
Sonnenschein	OPzV / A600	7 OPzV 490 / A602/490	2	M8	371006
Sonnenschein	OPzV / A600	8 OPzV 800 / A602/800	2	M8	371006
Sonnenschein	Solar Block	All	6 to 12	A-Terminal (SAE)	371001
Sonnenschein	Solar Series	6V 6 OGiV 192 / A706/192	6	M8	371006
Sonnenschein	Solar series	S12/(41-230)	12	A-Terminal (SAE)	None Supported
Sonnenschein	Solar Series	S12/17 G5	12	M5 (Supply M6)	371001
Sonnenschein	Solar Series	S12/27 G5	12	M5 (Supply M6)	371001
Sonnenschein	Solar Series	S12/32 G6	12	M6	371001
Sonnenschein	Solar Series	S12/6.6 S	12	Tab	None Supported
Sonnenschein	Solar Series	SB12/(60-185)	12	A-Terminal (SAE)	None Supported
Sonnenschein	Solar Series	SB6/(200-330)	6	A-Terminal (SAE)	None Supported
Sprinter	S Series	All	6 to 12	M6	371001
Yuasa	Genesis	NP0.8-12FR	12	Tab	None Supported

Tech20071030-1-4 Battery Tab Reference List

Yuasa	Genesis	NP1.2-12FR	12 Tab	None Supported
Yuasa	Genesis	NP1.2-6FR	6 Tab	None Supported
Yuasa	Genesis	NP10-6FR	6 Tab	None Supported
Yuasa	Genesis	NP12-12FR	12 Tab	None Supported
Yuasa	Genesis	NP12-6FR	6 Tab	None Supported
Yuasa	Genesis	NP2.3-12FR	12 Tab	None Supported
Yuasa	Genesis	NP2.6-12FR	12 Tab	None Supported
Yuasa	Genesis	NP2.8-6FR	6 Tab	None Supported
Yuasa	Genesis	NP2.9-12FR	12 Tab	None Supported
Yuasa	Genesis	NP2-12C	12 Tab	None Supported
Yuasa	Genesis	NP2-12FR	12 Tab	None Supported
Yuasa	Genesis	NP24-12FR	12 1/4"	371001
Yuasa	Genesis	NP3.4-12FR	12 Tab	None Supported
Yuasa	Genesis	NP3-12FR	12 Tab	None Supported
Yuasa	Genesis	NP3-6FR	6 Tab	None Supported
Yuasa	Genesis	NP38-12B	12 1/4"	371001
Yuasa	Genesis	NP4.5-6FR	6 Tab	None Supported
Yuasa	Genesis	NP4-12FR	12 Tab	None Supported
Yuasa	Genesis	NP4-6FR	6 Tab	None Supported
Yuasa	Genesis	NP5-12FR	12 Tab	None Supported
Yuasa	Genesis	NP5-6FR	6 Tab	None Supported
Yuasa	Genesis	NP7-12FR	12 Tab	None Supported
Yuasa	Genesis	NP7-6FR	6 Tab	None Supported
Yuasa	Genesis	NP8.5-6FR	6 Tab	None Supported
Yuasa	Genesis	NPH3.2-12FR	12 Tab	None Supported
Yuasa	Genesis	NPX-100B	12 10-32 UNF	371008
Yuasa	Genesis	NPX-150B	12 10-32 UNF	371008
Yuasa	Genesis	NPX-50FR	6 Tab	None Supported
Yuasa	Genesis	NPH2-12FR	12 Tab	None Supported
Yuasa	PowerSafe	SBS HB30	12	
Yuasa	Yuasa	EN 160-4	4 M8 F	371006

Tech20071030-1-4 Battery Tab Reference List

Yuasa	Yuasa	EN 160-6	6	M8 F	371006
Yuasa	Yuasa	EN 320-2	2	M8 F	371006
Yuasa	Yuasa	EN 480-2	2	M8 F	371006
Yuasa	Yuasa	EN 80-4	4	M8 M	371006
Yuasa	Yuasa	EN 80-6	6	M8 M	371006
Yuasa	Yuasa	EN100-6	6	M8 M	371006
Yuasa	Yuasa	EN100-6	6	M8	371006
Yuasa	Yuasa	EN160-6	6	M8	371006
Yuasa	Yuasa	EN320-2	2	M8	371006
Yuasa	Yuasa	EN480-2	2	M8	371006
Yuasa	Yuasa	EN80-6	6	M8	371006
Yuasa	Yuasa	ENL 100-4	4	M8 M	371006
Yuasa	Yuasa	ENL 100-6	6	M8 M	371006
Yuasa	Yuasa	ENL 160-6	6	M8 F	371006
Yuasa	Yuasa	NP 17-12	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NP 18-12	12	5.5mm	371001
Yuasa	Yuasa	NP 24-12I	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NP 38-12I	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NP 65-12I	12	M6	371001
Yuasa	Yuasa	NP Series (below 17)	6 to 12	Tab	None Supported
Yuasa	Yuasa	NP10-6	6	Tab	None Supported
Yuasa	Yuasa	NP12-12	12	Tab	None Supported
Yuasa	Yuasa	NP17-12	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NP24-12	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NP38-12	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NP4-12	12	Tab	None Supported
Yuasa	Yuasa	NP7-12	12	Tab	None Supported
Yuasa	Yuasa	NP7-6	6	Tab	None Supported
Yuasa	Yuasa	NPC 17-12	12	5.5 mm	371001
Yuasa	Yuasa	NPC 24-12I	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NPC 30-12	12	5.5 mm	371001

Tech20071030-1-4 Battery Tab Reference List

Yuasa	Yuasa	NPC 38-12I	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NPC 65-12I	12	M6	371001
Yuasa	Yuasa	NPL 100-12	12	11mm	None Supported
Yuasa	Yuasa	NPL 130-6IFR	6	M5 (Supply M6)	371001
Yuasa	Yuasa	NPL 200-6	6	11mm	None Supported
Yuasa	Yuasa	NPL 24-12I	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NPL 38-12I	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NPL 65-12I	12	M6	371001
Yuasa	Yuasa	NPL 78-12IFR	12	M8	371006
Yuasa	Yuasa	NPL100-12	12	M10 (Special)	371008
Yuasa	Yuasa	NPL200-6	6	M10 (Special)	371008
Yuasa	Yuasa	NPL24-12I	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NPL24-12IFR	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NPL38-12	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NPL38-12IFR	12	M5 (Supply M6)	371001
Yuasa	Yuasa	NPL65-12	12	M6	371001
Yuasa	Yuasa	NPL65-12IFR	12	M6	371001
Yuasa	Yuasa	NPL78-12IFR	12	M8	371006
Yuasa	Yuasa	SW200	12	N/A	
Yuasa	Yuasa	SWL 1100	12	M5 (Supply M6)	371001
Yuasa	Yuasa	SWL 1800	12	M6	371001
Yuasa	Yuasa	SWL 1850	12	M6	371001
Yuasa	Yuasa	SWL 1850-6	6	M6	371001
Yuasa	Yuasa	SWL 2250	12	M8	371006
Yuasa	Yuasa	SWL 2500	12	M6	371001
Yuasa	Yuasa	SWL 750	12	M5 (Supply M6)	371001
Yuasa	Yuasa	SWL1100	12	M5 (Supply M6)	371001
Yuasa	Yuasa	SWL1100FR	12	M5 (Supply M6)	371001
Yuasa	Yuasa	SWL1850	12	M6	371001
Yuasa	Yuasa	SWL1850-12IFR	12	M6	371001
Yuasa	Yuasa	SWL1850-6	6	M6	371001

Tech20071030-1-4 Battery Tab Reference List

Yuasa	Yuasa	SWL2250FR	12	M6	371001
Yuasa	Yuasa	SWL2300	12	M5 (Supply M6)	371001
Yuasa	Yuasa	SWL2500FR	12	M6	371001
Yuasa	Yuasa	SWL750	12	M5 (Supply M6)	371001
Yuasa	Yuasa	SWL750FR	12	M5 (Supply M6)	371001
Yuasa	Yuasa	UXF 100-12	12	unknown	None Supported
Yuasa	Yuasa	UXF 150-12	12	unknown	None Supported